MR 85

AM - FM STEREO TUNER

McIntosh

The Compendium

FRONT PANEL: **Glass with illuminated teal/gold nomenclature. PRESET control. Digital readout: preset station tuned, frequency display, broadcast band and signal strength. FM stereo signal light. TUNING control. 7 Push buttons: ENTER (with indicator), DISPLAY, SPATIAL (with indicator), MONO, TUNER 1 or 2, AM or FM, , SEEK, SEEK • , AUTOMUTE (with indicator), STANDBY/ON (with indicator), POWER ON or OFF. Additional AM/FM TM 1 tuner is optional.**

BACK PANEL: **ANTENNA 1: external AM ANTenna (RAA1) and 75 Ω FM ANTenna coax input. TUNER 1 OUTPUT LEVEL control. Left & right TUNER 1 VARIABLE and FIXED OUTPUTS. POWER CONTROL IN and OUT. Power cord receptacle. DATA IN jacks for TUNER 1 and 2. Left & right TUNER 2 VARIABLE and FIXED OUTPUTS. TUNER 2 OUTPUT LEVEL control. Spaces reserved for optional TM 1 second tuner module: ANTENNA 2: external AM ANTenna (RAA1) and 75 Ω FM ANTenna coax input.**

FM SECTION: ***Sensitivity:*** **14dBF or 1.4uV across 75 ohms.** ***Stereo 50dB Quieting Sensitivity:*** **35dBF or 15uV across 75 ohms.** ***Response:*** **20-15kHz (+0 -1dB).** ***Distortion:*** **0.45% in stereo.** ***Capture Ratio:*** **1.2dB.** ***Image Rejection:*** **75dB. S/N: 70dB stereo.** ***Alternate Channel Selectivity:*** **75dB.** ***Separation:*** **45dB.** ***Spurious Rejection:*** **100dB.**

AM SECTION: ***Sensitivity:*** **20uV.** ***Response:*** **50-6kHz NRSC.** ***Distortion:*** **0.5%.** ***Adjacent Channel Selectivity:*** **45dB.** ***S/N:*** **58dB.** ***Image Rejection:*** **65dB.**

Power Requirements: **120V at 20 Watts.**

OTHER: **Optional TM 1 second tuner can be mounted inside of chassis.**

MR 85 - Sold from 2000 - 2010. S/N: SE1001~SE????

Size: **5.44"H, 17.5"W and 17.5"D behind panel.** ***Weight:*** **25.5 lb.** ***$1,950.00***